

# Power Star AVR



- 8pc Outlets for Nema Type
- Automatically Regulating High Voltage and Low Voltage
- Internet, ADSL, Tel/Fax Data Line Surge Protection
- Able to reset Input Overload Protection Circuit Breaker
- User-friendly Visual Indicators Display
- USB Port
- Child Protector
- Wall Mount Holes

## Power Star AVR Selection Guide

MODEL	PS1200	PS1500	PS2200
CAPACITY	1200VA	1500VA	2200VA
<b>INPUT</b>			
Voltage	220VAC		
Voltage Range	175VAC ~ 273VAC (-30% +25%)		
Frequency Range	60Hz		
<b>OUTPUT</b>			
Voltage Regulation	207VAC ~ 253VAC (+/-10%)		
Modem/ Phone Line Surge Protection	RJ-45/RJ-11		
Receptacles	8 (4 for AVR protection and 4 for extended use)		
<b>INDICATORS</b>			
Power LED	Yellow lighting		
AVR LED	Green lighting		
AVR LED	Yellow lighting		
<b>PHYSICAL</b>			
Dimension, D x W x H (mm)	248*90*87.5mm		
Net Weight (kgs)	1.14	1.54	1.96
<b>ENVIRONMENT</b>			
Humidity	0-95 % RH @ 0- 40°C (non-condensing)		
Noise Level	Less than 40dB		